



# Solution Concentrations

## Goals

- ✓ Create solutions of different concentrations
- ✓ Use solutions to run a salt water battery
- ✓ Make calculations based on solution data

## Background

Combining two substances doesn't have to result in a chemical reaction. It's possible to mix substances and have them form a mixture instead of a compound. Mixtures are classified based on how the substances interact when mixed together.

Heterogeneous mixtures still have different parts visible (like if you shake up oil and vinegar salad dressing) while homogeneous mixtures appear to be the same throughout (like air, which is a mixture of nitrogen, oxygen, carbon dioxide, and trace gases).

Solutions are a special type of homogeneous mixture where the particles of the substance being dissolved are so small that they can't be separated from the mixture by straining or centrifuging. Salt in water is a perfect example: once the salt has dissolved in the water, it can't be removed unless the water is evaporated.

Dissolved salt splits into sodium ( $\text{Na}^+$ ) and chloride ( $\text{Cl}^-$ ) ions. The presence of these ions in the water makes it easier for an electric current to flow. This allows us to generate electricity by pumping electrons from the magnesium anode to the cathode (which is actually the air) through the wires, just like a battery. If you don't remember what anodes and cathodes are, read more about electrodes in Introduction to Batteries.

The concentration of a solution can be expressed as a percentage ratio (mass of solute/volume of solvent) or as a molar ratio such as molarity (moles of solute/volume of solvent) or molality (moles of solute/mass of solvent).

During this activity, you will use a solution of salt in water to run a battery and generate an electric current.

## Procedure

1. Get salt water solution from your teacher and put it in the graduated cylinder. Make sure to get at least 25mL. And be careful, it's hot!
2. Using the syringe, transfer 15mL of the salt water solution into the bottom of your battery.
3. Snap the blue top of the battery onto the white bottom.
4. Attach one red wire to two red plugs on the left and right sides of the battery at the back.
5. Connect the wires from the motor to the red and black plugs nearest to them on the front of the frame.
6. Connect the loose wires from the battery to the other plugs on the front of the frame.
7. Use the stopwatch to time how long your car takes to complete the track. Repeat and record your results in the table below.
8. When you're finished with the salt water battery, rinse the top and bottom with distilled water.



# Solution Concentrations



## Observations

## Data Table

Trial	Time (sec):	Observations:
1		
2		
3		



## Experimentation

1. Prepare solutions of salt water according to the following concentrations. Record how much salt you used in each concentration below:

Concentration:	g NaCl:	mL H <sub>2</sub> O:
4%	1	25mL
8%	2	25mL
12%	3	25mL
16%	4	25mL
20%	5	25mL



## Solution Concentrations

2. Using the different concentrations of salt water solution, use the battery to power the motor as in the Procedure section. Observe what happens each time and record your results below. Be sure to rinse out the salt water from the battery after each trial.

Concentration:	Time (sec):	Observations:
4%		
8%		
12%		
16%		
20%		

3. Using salt water of different temperature, run the battery like you did in the Procedure section, using the same concentration each time. Write your observations below.

Temperature (°C):	Time (sec):	Observations:



### Measurement

For this section, you will need a multimeter or the Horizon Renewable Energy Monitor. For an introduction to using a multimeter, [click here](#).

1. Raise the front wheels off the ground and measure the current in amps and the voltage in volts while running the battery at different concentrations of salt. Record your answers below:



## Solution Concentrations

Concentration:	Current (A):	Voltage (V):
4%		
8%		
12%		
16%		
20%		

2. Voltage is equal to the current multiplied by the resistance ( $V = IR$ ), so according to your data what is the resistance of the fan motor?

Resistance: \_\_\_\_\_  $\Omega$

3. Measure the current in Amps and the voltage in Volts while running the battery with different temperatures of salt water. Record your answers below:

Temperature ( $^{\circ}\text{C}$ ):	Time (sec):	Observations:

4. Construct an explanation of what you observed as you tested salt water solutions of different temperatures.



# Solution Concentrations



## Analysis

1. Make a scientific claim about what you observed while running your battery.
2. What evidence do you have to back up your scientific claim?
3. What reasoning did you use to support your claim?
4. Design an experiment that would determine the volume of salt water solution that would produce the most electric current. Describe your experiment below:

